



MT532 SMS Commands List

Function	Commands Format	Example	Reply	Note
Set first pre-saved number	101#phone number#	101#13424392330#	OK	
Set second pre-saved number	102#phone number#	102#13424392330#	OK	
Set third pre-saved number	103#phone number#	103#13424392330#	OK	
Delete first pre-saved number	D101#	D101#	OK	
Delete second pre-saved number	D102#	D102#	OK	
Delete third pre-saved number	D103#	D103#	OK	
Checking pre-saved numbers	C10#	C10#	101#phone102#phone103#phone	
Set Password	password,old password,new password	password,123456,000000	passwor ok	
Google Map link	G1234	http://maps.google.com/maps?q=+22.64820,+114.03433 ID:9175387837 ACC:ON GPS:A Speed:0.00KM/H 23-09-15 11:35:17		
Over Speet Alert	speed,password,speed value	speed,123456,080	speed ok	080mean 80KM/H; 000 mean close over speed, Speed range is [0,255] KM/H
Disable phone alarm for shake	121#	121#	OK	
Enable phone alarm for shake	122#	122#	OK	
Enable SMS alarm for shake	125#	125#	OK	
Disable SMS alarm for shake	126#	126#	OK	
Set APN	apn,password,apn	apn,123456,cmnet	apn ok	APN username and password are blank (not filled in).
Set APN Username	apnuser123456 user		apnuser ok	APN username is required
Set APN Password	apnpasswd123456 password		apnpasswd ok	APN password is required
Set IP/Port	IP+space+ IP+ space+ port number	IP 113.98.254.180 8185	SET OK	SET IP PORT
Set timezone	zone,password,Timezone	zone,123456,E08	OK	Set timezone, E08: mean east 8 time zone
Enable ACC Illegal SMS Alarm	accsms,password,1	accsms,123456,1	acc sms alarm set ok	
Disable ACC Illegal SMS Alarm	accsms,password,0	accsms,123456,0	acc sms alarm set ok	
Enable ACC Illegal Phone Alarm	accall,password,1	accall,123456,1	acc call alarm set ok	
Disable ACC Illegal Phone Alarm	accall,password,0	accall,123456,0	acc call alarm set ok	
ACC ON Interval	FREQ,123456,60		OK	10-65535 seconds
ACC OFF Interval	STATIC,123456,120		OK	10-65535 seconds
Heart Beat Interval	sleep,123456,240		OK	10-65535 seconds
Reboot GPS	CQGPS		GPS reset OK!	Restart GPS
Reboot device	CQ		system reset OK!	Restart Device
Reset	FORMAT		OK	Reset Device
Read Config	CXZT			Checking device setting