



MT909 SMS Commands List

Function	Commands Format	Example	Reply	Note
Set first pre-saved number	101#phone number#	101#13424392330#	OK	
Set second pre-saved number	102#phone number#	102#13424392330#	OK	
Set third pre-saved number	103#phone number#	103#13424392330#	OK	
Delete first pre-saved number	D101#	D101#	OK	
Delete second pre-saved number	D102#	D102#	OK	
Delete third pre-saved number	D103#	D103#	OK	
Set Password	password,old password,new password	password,123456,000000	password ok	
Google Map link	G1234		https://maps.google.com/maps?q=+22.64819,+114.03435 ID:7026181031 ACC:OFF GPS:A Speed:0.00KM/H 25.06.23 15:35:23	
Over Speed Alert	speed,password,speed value	speed,123456,080	speed ok	080 mean 80KM/H; 000 mean close over speed.Speed range is [0,255] KM/H
Disable phone alarm for shake	121#	121#	OK	
Enable phone alarm for shake	122#	122#	OK	
Enable SMS alarm for shake	125#	125#	OK	
Disable SMS alarm for shake	126#	126#	OK	
Set APN	apn,password,apn	apn,123456,iot.1nce.net	apn ok	APN username and password are blank (not filled in).
Set APN Username	apnuser,password,user	apnuser,123456,internet	apnuser ok	APN username is required
Set APN Password	apnpasswd,password,password	apnpasswd,123456,internet	apnpasswd ok	APN password is required
Set IP/Port	IP+space+ IP+ space+ port number	IP 113.98.254.180 8185	SET OK	SET IP PORT
Set timezone	zone,password,Timezone	zone,123456,E08	OK	Set timezone, E08: mean east 8 time zone
Normal Mode	nmod,password	nmod,123456	OK	
Smart Mode	tmod,password,T	tmod,123456,5	OK	
Power Saving Mode	mod,password	smod,123456	OK	
Setup Interval Time from Wake Up	FREQ,password,T	FREQ,123456,60	OK	10-65535 seconds
Set Sleep Time	sleep,password,T	sleep,123456,3	OK	1-1440 minutes
Heart Beat Interval	interval,password,T	interval,123456,65535	OK	10-65535 seconds
Reboot device	CQ		system reset OK!	Restart Device
Reset	FORMAT		SET OK	Reset Device
Read Config	CXZT			Checking device setting